

OMNITRONIC CFL-1242 Live mixer

12-channel live mixer

Art.n.: 10060300

GTIN: 4026397304725



L'articolo non è più disponibile.

Descrizione :

Something for everybody. The smallest unit of this CFL live mixer series disposes of 12, the biggest unit disposes of 32 mono inputs. Normally, live mixers have faders from 70 - 80 mm. The CFL series has remarkably long faders that easily reach 100 mm. Although it is very low-priced, the series is highly resistant and by offering four subgroups and four Aux-Sends it is really well equipped. In total: powerful but not pricy.

Logistica

EAN / GTIN: 4026397304725

Peso : 15,45 kg

Lunghezza : 0.73 m

Larghezza : 0.26 m

Altezza : 0.68 m

Features :

- 12 mono inputs with XLR sockets and balanced line inputs
- +48V phantom power per channel
- 2 stereo inputs via balanced jacks
- 2 stereo effect returns
- Insert for every mono channel
- High pass filter and 3-band EQ with semi-parametric mids for all mono inputs
- 4 groups for levelling complete signal groups (e.g. drums)
- Mutes for every channel
- 4 aux send (2 pre, 2 post) per channel for controlling the effects and for monitoring
- Separate master, group, monitor outputs
- 100 mm faders
- Precise 12-digit LED meter in subgroups and stereo master

Dati tecnici :

Alimentazione elettrica: 115/230 V AC, 50/60 Hz

Potenza totale installata:	40,00 W
Misure:	Larghezza: 53 cm Profondità: 53 cm Altezza: 16 cm
Peso:	12,80 kg
Inputs:	
12 mono	XLR or balanced 6.3 mm jacks
12 inserts	6.3 mm jacks
2 stereo	6.3 mm jacks
4 Aux-Return	balanced 6.3 mm jacks
Outputs:	
2 Main Out:	XLR or balanced 6.3 mm jacks
1 Monitor	balanced 6.3 mm jack
4 Aux Send:	balanced 6.3 mm jack
Rec Out	RCA
Frequency range:	10-60000 Hz, ± 3 dB
Dimensions (W x D x H):	530 x 530 x 160 mm