

OMNITRONIC SLM-600 SPL Meter

Digital sound level meter with software kit

Art.n.: 10360609

GTIN: 4026397467215



Features :

- Digital sound level meter with LCD
- Software kit for data recording and analysis on PCs and laptops
- Supports Windows XP, vista and 7 (32 bit)
- Data transfer via USB port
- Electret condenser microphone cartridge
- Measuring range from 30-130 dB
- Max Hold function
- A and C weighting
- Slow and fast measuring mode
- Additional analog outputs for AC and DC current via 3.5 mm jacks (1/8")
- Operation via 4 x 1.5 V mignon battery (type AA) or USB bus
- Incl. windscreen, batteries, USB cable, software (CD-ROM)
- Funzionamento a pila/batteria ricaricabile possibile

Logistica

EAN / GTIN: 4026397467215

Peso : 0,91 kg

Lunghezza : 0.28 m

Larghezza : 0.25 m

Altezza : 0.07 m

Dati tecnici :

Pila:	4 x 1.5 V AA Mignon LR06 alkaline manganese presente
Intervallo di frequenza:	31,5 - 8500 Hz
Misure:	Larghezza: 14,5 cm Profondità: 6 cm Altezza: 11 cm
Peso:	0,80 kg

Power supply:	4 x 1.5 V battery, type AA
	or 5 V DC, 100 mA via USB port
Measuring ranges:	30-80 dB, 40-90 dB, 50-100 dB, 60-110 dB, 70-120 dB, 80-130 dB, 30-130 dB
Accuracy:	±1.5 dB/94 dB, 1kHz
Level weighting:	A or C
Microphone:	electret condenser microphone
AC output:	0.707 V RMS
Output impedance:	600 ohms
DC output:	10 mV
Output impedance:	100 ohms
Supported operating systems:	Windows XP, Vista, 7 (32 bit)

Contenuto della confezione:
