

EUROLITE LED Strip RGB RF Controller

Controller LED a 3 canali con telecomando radio per strisce LED RGB 12-24 V

Art.n.: 50531103

GTIN: 4026397637465



Descrizione :

Controller with wireless remote control for LED strips

Use the EUROLITE LED Strip RGB RF Controller to control your RGB LED strips for 12 to 24 volts. The supplied ergonomic, user-friendly remote control with touch-sensitive color wheel is well designed so that you can select the color conveniently.

The controller offers you ten integrated programs - you can also adjust the speed and brightness.

If the remote control is not used for a longer period of time, it automatically switches to standby mode. A simple movement or slight shaking turns the remote on again. This function increases the life of the three micro-batteries included in the package.

The range is up to 20 meters.

Features :

- Per il controllo di strisce LED RGB 12-24 V
- Selezione del colore tramite una ruota dei colori sensibile al tatto
- Prese RJ45 per il collegamento in serie
- Dimmer elettronico; Velocità di srotolamento regolabile
- 10 programmi di spettacolo integrati
- Controllabile via radiocomando
- Portata fino a 20m

Logistica

EAN / GTIN: 4026397637465

Peso : 0,32 kg

Lunghezza : 0.11 m

Larghezza : 0.11 m

Altezza : 0.05 m

Dati tecnici :

Alimentazione elettrica:	12/24V DC
Potenza totale installata:	Massimo 360 W 12 V DC Massimo 720 W 24 V DC 120 W 12 V DC per canale 240 W 24 V DC per canale
Corrente in uscita:	Max. 3 x 10 A per canale
Allacciamento elettrico:	Alimentazione dell'energia elettrica tramite terminale a vite
Uscita di corrente:	4 x terminale a vite
Pila:	Micro (AAA) (non in dotazione)
Attivazione:	Radiocomando
Massima:	Fino a 20m
Deviazione della portante:	433,920 MHz
Collegamenti:	Segnale via 2 x RJ-45 (F) versione da incasso Terminale a vite
Misure:	Lunghezza: 9 cm Larghezza: 9 cm Altezza: 2,4 cm
Peso:	0,29 kg
Misure:	Altezza: 2,2 cm

Contenuto della confezione:

1 x Controller
1 x Trasmettitore
1 x Manuale d'uso
1 x dichiarazione di conformità