

EUROLITE LVH-3 AV switch

Manual AV switch 4:1

Art.n.: 81013203

GTIN: 4026397324792



Descrizione :

MANUAL AV SWITCH 4:1

The LVH-3 was designed to switch video and stereo audio signals from up to four sources to one output. Switching can be made manually with four push buttons or with an external remote control. A control LED indicates which channel is active. Inputs and outputs are made on the front panel via RCA jacks. Power connections are made using either the block terminals or a DC power jack. The unit is compatible with NTSC and PAL systems.

Logistica

EAN / GTIN: 4026397324792

Peso : 0,50 kg

Lunghezza : 0.17 m

Larghezza : 0.10 m

Altezza : 0.06 m

Features :

- Video and stereo audio signal switching from four sources to one output
- Switching via durable keyboard-style buttons
- Active channel indication via control LED
- Block terminals for remote control
- NTSC and PAL compatible
- High quality gold-plated RCA connectors
- Super compact metal housing

Dati tecnici :

Alimentazione elettrica: 12-24V DC 100 mA

Allacciamento elettrico: Alimentazione dell'energia elettrica tramite terminale a vite

Alimentazione dell'energia elettrica tramite connettore cavo (M) versione da incasso

Intervallo di frequenza:	10 - 10000000 Hz
Rapporto segnale-rumore:	>-95 dB
Distorsione armonica totale:	<0,01 % a 1 kHz
Misure:	Larghezza: 14,6 cm Profondità: 9 cm Altezza: 4,2 cm
Peso:	0,44 kg
Video:	
4 x inputs:	1 Vpp/ 75 ohms, composite RCA
1 x outputs:	1 Vpp/ 75 ohms, composite RCA
Off attenuation:	>78 dB
Differential gain:	0.1%
Differential phase:	<0.3°
Audio:	
4 x inputs:	10 kohms, stereo RCA
1 x output:	75 ohms, stereo RCA
Gain:	nominal 0 dB
Input level:	-10 dBV nominal
Headroom:	>20 dB/ -10 dBV
Off attenuation	>74 dB
Crosstalk:	below noise floor (inputs terminated)

Contenuto della confezione:
